

DESCRIPTION

Model SA-1A is a sound activated switch used in conjunction with the LOUROE ASK-4® #101 Audio Monitoring System or any of the AP Series non-alarming base stations. Usually located near the base station, the SA-1A provides a variable threshold level control that activates the microphone when that level is exceeded by a sound. In addition, it has 2 sets of relay contacts that automatically close when the threshold level is exceeded. This can be used to activate a camera, light or other annunciation. Automatic re-set is adjustable between 0.5 and 60 seconds. An alarm LED is illuminated during activation time. 12 Vdc Power is required.



SA-1A

APPLICATION

- Unattended Facilities
- Warehouses
- Entry Gates
- Remote Locations
- Therapy Labs
- Stables




AD-1 POWER SUPPLY (2) RCA SINGLE CABLES

FEATURES

- Adjustable threshold level control
- Two relay contacts for activating cameras, lights, machinery, etc.
- Adjustable re-set from 0.5 to 60 seconds
- Alarm LED indicator
- Automatic electronic switch to pass audio to base station
- Receptacle for 12 Vdc power

IMPORTANT NOTICE
 When this equipment is used as part of an audio monitoring system, the law requires that the public be given notice of AUDIO MONITORING ON THE PREMISES. A decal notice is included with each microphone shipped.




Federal Law References:
 Federal Regulations, US Code, Title 18.
 Crime and Criminal Procedure, Sec 2510.

WIRING REQUIREMENTS

2 Conductor **shielded** cable, 22 gauge with a 24 gauge drain wire

NOTE: Unshielded cable is not satisfactory for audio systems

West Penn 452 or equivalent



SPECIFICATIONS

■ Current drain	70 mA
■ Audio input impedance	10KΩ
■ Relay contact	5A @ 277 Vac or 5A @ 30Vdc
■ DC input	12Vdc, 500mA
■ Relay latch time	0.5 to 60 seconds
■ Dimensions	6 1/8"L x 4 5/8"W x 1 7/8"H
■ Weight	7 oz
■ Shipping Weight	1lb

